

LM236-2.5, LM336-2.5 2.5-V INTEGRATED REFERENCE CIRCUITS

SLVS063B – NOVEMBER 1988 – REVISED JULY 1999



- Low Temperature Coefficient
- Wide Operating Current . . . 400 μ A to 10 mA
- 0.27- Ω Dynamic Impedance
- $\pm 1\%$ Tolerance Available
- Specified Temperature Stability
- Easily Trimmed for Minimum Temperature Drift
- Fast Turnon
- Three-Lead Transistor Package

description


The LM236-2.5 and LM336-2.5 integrated circuits are precision 2.5-V shunt regulator diodes. These monolithic references operate as low-temperature-coefficient 2.5-V zeners with a 0.2- Ω dynamic impedance. A third terminal provided on the circuit allows the reference voltage and temperature coefficient to be easily trimmed.

The series is useful as precision 2.5-V low-voltage references (V_Z) for digital voltmeters, power supplies, or operational-amplifier circuitry. The 2.5-V voltage reference makes it convenient to obtain a stable reference from 5-V logic supplies. Devices in this series operate as shunt regulators, and can be used as either positive or negative voltage references.

The LM236-2.5 is characterized for operation from -25°C to 85°C . The LM336-2.5 is characterized for operation from 0°C to 70°C .



symbol



AVAILABLE OPTIONS

T _A	PACKAGED DEVICES		CHIP FORM (Y)
	SMALL OUTLINE (D)	PLASTIC (LP)	
0°C to 70°C	LM336D-2.5	LM336LP-2.5	LM336Y-2.5
-25°C to 85°C	LM236D-2.5	LM236LP-2.5	—

The D package is available taped and reeled. Add the suffix R to the device type (i.e., LM336DR-2.5). Chip forms are tested at 25°C.



Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

PRODUCTION DATA information is current as of publication date. Products conform to specifications per the terms of Texas Instruments standard warranty. Production processing does not necessarily include testing of all parameters.

 **TEXAS
INSTRUMENTS**

POST OFFICE BOX 655303 • DALLAS, TEXAS 75265


Copyright © 1999, Texas Instruments Incorporated

LM236-2.5, LM336-2.5

2.5-V INTEGRATED REFERENCE CIRCUITS

SLVS063B – NOVEMBER 1988 – REVISED JULY 1999

schematic diagram



absolute maximum ratings over operating free-air temperature range (unless otherwise noted)†

Reverse current, I_R	20 mA
Forward current, I_F	10 mA
Package thermal impedance, θ_{JA} (see Notes 1 and 2): D package	97°C/W
LP package	156°C/W
Lead temperature 1,6 mm (1/16 inch) from case for 10 seconds: D or LP package	260°C
Storage temperature range, T_{stg}	-65°C to 150°C

† Stresses beyond those listed under “absolute maximum ratings” may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under “recommended operating conditions” is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

- NOTES: 1. Maximum power dissipation is a function of $T_J(max)$, θ_{JA} , and T_A . The maximum allowable power dissipation at any allowable ambient temperature is $P_D = (T_J(max) - T_A)/\theta_{JA}$. Operating at the absolute maximum T_J of 150°C can impact reliability.
2. The package thermal impedance is calculated in accordance with JESD 51, except for through-hole packages, which use a trace length of zero.

recommended operating conditions

		MIN	MAX	UNIT
Operating free-air temperature, T_A	LM236-2.5	-25	85	°C
	LM336-2.5	0	70	



POST OFFICE BOX 655303 • DALLAS, TEXAS 75265

LM236-2.5, LM336-2.5 2.5-V INTEGRATED REFERENCE CIRCUITS

SLVS063B – NOVEMBER 1988 – REVISED JULY 1999

electrical characteristics at specified free-air temperature (unless otherwise noted)

PARAMETER	TEST CONDITIONS	T _A †	LM236-2.5			LM336-2.5			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
V _Z Reference voltage	I _Z = 1 mA	25°C	LM236, LM336			LM336A, LM336B			V
			2.44	2.49	2.54	2.39	2.49	2.59	
ΔV _Z (ΔT)	V _Z adjusted to 2.490 V, I _Z = 1 mA	Full range		3.5	9		1.8	6	mV
ΔV _Z (ΔI)		25°C		2.6	6		2.6	10	mV
	I _Z = 400 μA to 10 mA	Full range		3	10		3	12	
ΔV _Z (Δt)		I _Z = 1 mA	25°C		20			20	ppm/khr
z _Z Reference impedance	I _Z = 1 mA, f = 1 kHz		25°C		0.2	0.6		0.2	1
		Full range		0.4	1		0.4	1.4	

† Full range is –25°C to 85°C for the LM236-2.5 and 0°C to 70°C for the LM336-2.5.

electrical characteristics, T_A = 25°C

PARAMETER	TEST CONDITIONS	LM336Y-2.5			UNIT
		MIN	TYP	MAX	
V _Z Reference voltage	I _Z = 1 mA	2.39	2.49	2.59	V
ΔV _Z (ΔI)	I _Z = 400 μA to 10 mA		2.6	10	mV
ΔV _Z (Δt)	I _Z = 1 mA		20		ppm/khr
z _Z Reference impedance	I _Z = 1 mA, f = 1 kHz		0.2	1	Ω



LM236-2.5, LM336-2.5

2.5-V INTEGRATED REFERENCE CIRCUITS

SLVS063B – NOVEMBER 1988 – REVISED JULY 1999

TYPICAL CHARACTERISTICS

CHANGE IN REFERENCE VOLTAGE
vs
REFERENCE CURRENT




Figure 1

NOISE VOLTAGE
vs
FREQUENCY




Figure 2

REFERENCE IMPEDANCE
vs
FREQUENCY




Figure 3

APPLICATION INFORMATION




Figure 4. 2.5-V Reference




Figure 5. 2.5-V Reference With Minimum Temperature Coefficient




Figure 6. Wide-Input-Range Reference

IMPORTANT NOTICE

Texas Instruments and its subsidiaries (TI) reserve the right to make changes to their products or to discontinue any product or service without notice, and advise customers to obtain the latest version of relevant information to verify, before placing orders, that information being relied on is current and complete. All products are sold subject to the terms and conditions of sale supplied at the time of order acknowledgement, including those pertaining to warranty, patent infringement, and limitation of liability.

TI warrants performance of its semiconductor products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are utilized to the extent TI deems necessary to support this warranty. Specific testing of all parameters of each device is not necessarily performed, except those mandated by government requirements.

CERTAIN APPLICATIONS USING SEMICONDUCTOR PRODUCTS MAY INVOLVE POTENTIAL RISKS OF DEATH, PERSONAL INJURY, OR SEVERE PROPERTY OR ENVIRONMENTAL DAMAGE ("CRITICAL APPLICATIONS"). TI SEMICONDUCTOR PRODUCTS ARE NOT DESIGNED, AUTHORIZED, OR WARRANTED TO BE SUITABLE FOR USE IN LIFE-SUPPORT DEVICES OR SYSTEMS OR OTHER CRITICAL APPLICATIONS. INCLUSION OF TI PRODUCTS IN SUCH APPLICATIONS IS UNDERSTOOD TO BE FULLY AT THE CUSTOMER'S RISK.

In order to minimize risks associated with the customer's applications, adequate design and operating safeguards must be provided by the customer to minimize inherent or procedural hazards.

TI assumes no liability for applications assistance or customer product design. TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right of TI covering or relating to any combination, machine, or process in which such semiconductor products or services might be or are used. TI's publication of information regarding any third party's products or services does not constitute TI's approval, warranty or endorsement thereof.

This datasheet has been downloaded from:

www.DatasheetCatalog.com

Datasheets for electronic components.